



BOYI H60 Pro Aluminum Magnetic Switch Keyboard



Quick Start Guide
Made In China

FN Combination Shortcut: Windows / Mac System

Key Combination	WIN	MAC
FN+1!	F1	Screen Brightness -
FN+2@	F2	Screen Brightness +
FN+3#	F3	Dispatch Center
FN+4\$	F4	Launch Pad
FN+5%	F5	F5
FN+6^	F6	F6
FN+7&	F7	Previous Song
FN+8*	F8	Play/Pause
FN+9(F9	Next Song
FN+0)	F10	Mute
FN+-_	F11	Volume -
FN+=+	F12	Volume +
FN+WIN-L	Lock/unlock WIN/APP key (White light always indicates when WIN key is locked)	
FN+T:	Prtsc	
FN+Y:	Scroll	
FN+U:	Pause	
FN+F:	Ins	
FN+G:	Home	
FN+H:	Page Up	
FN+N:	End	
FN+M:	Page Down	

Press and hold FN+CTRL-L for 3s: The first row of keys 1 - = functions are converted to F1-F12. The whole keyboard blinks red three times after successful conversion (repeat the operation of the key combination once more, and the functions of the keys will be restored)

Key Combination	FN+F1	FN+F2	FN+F3	FN+F4	FN+F5	FN+F6	FN+F7	FN+F8	FN+F9	FN+F10	FN+F11	FN+F12
Function	1	2	3	4	5	6	7	8	9	10	--	=

Universal Key Combinations

Key Combination	Function
FN+ESC	`
FN+SHIFT+ESC	~
FN+Z	WIN system
FN+X	MAC system (Backlight white light blinking)
FN+[18 Backlight mode switching
FN+ENTER	Turn off/on the backlight
FN +]	Keyboard brightness +
FN + [(Keyboard brightness -
FN + ::	Lighting effect speed -
FN + '"	Lighting effect speed +
FN + <.	Light color effect switching
FN+Spacebar	Long press about 3S to restore factory setting
FN+I	I J K L to up, left, down, right arrow keys function, click FN+I to return to normal
FN+BACK	Delete



BOYI

Driver Download And Firmware Upgrade

Visit the BOYI Official Website:

<https://www.boyikeyboard.com/Software-Driver.html>

Web Driver Link: <https://qmk.top/beta/>

Mode:BOYI H60 Pro

Input Mode: TYPE-C Wired

Number of Keys: 61Keys

Size: 12x5.1x1.7 inch

Keyboard Weight: 1.8 lb

If you have any issues or concerned things, please feel free to e-mail us:
(boyiservice2020@163.com) ☺